

LEOPARD



TX1

T80-Leopard transmitter TX1	
Article number:	T80TX-MX-10B
Application areas:	Hoisting equipment
Frequency:	433 - 434 MHz (69 channels)
Mod. Type:	Narrow band FM-modulation
Coding:	Digital pulse code
Code comb.:	262.143 (factory coded)
Functions:	4 x 2 or 6 x 1, On / Off
Radio type:	Double superheterodyne
Output:	10 mW (50 ohm)
Antenna:	Built-in
Power supply:	Rechargeable battery
Operating time:	Apr. 30 hours. Continuously
Weight:	Apr. 270 g (0.59 lb)
Dimensions:	160 x 70 x 35 mm (6.29 x 2.76 x 1.38 in)
Protection:	IP 54
Recommended receiver:	Receiver T80-Leopard RX1 and RX2

TELE RADIO AB

Sweden, Main office
Tel. +46 (0)31-748 54 60
e-mail: info@tele-radio.com

www.tele-radio.com

TELE RADIO SVERIGE

Sweden
Tel. +46 (0)31-724 98 00
e-mail: sverige@tele-radio.com

TELE RADIO OÜ

Estonia
Tel. +372 44 511 55
e-mail: m.jyrissoo@tele-radio.com

TELE RADIO GmbH

Germany
Tel. +49 (0)94 51-944 8 550
e-mail: kontakt@tele-radio-gmbh.de

TELE RADIO ASIA

China
Tel. +86-(0)592-3111168
e-mail: b.sun@tele-radio.cn

TELE RADIO TURKEY

Turkey
Tel. +90-532 292 4448
e-mail: c.mevlevioglu@tele-radio.com

TELE RADIO LTD

England
Tel. +44 (0) 1625 509125
e-mail: sales@teleradiouk.com

TELE RADIO LLC

North America & Latin America
Tel. +1 (305) 459 0763
e-mail: america@tele-radio.com

TELE RADIO BV

Benelux
Tel. +31-(0)70-419 41 20
e-mail: info@teleradio.nl

TELE RADIO AS

Norway
Tel. +47-6933 4900
e-mail: norway@tele-radio.com