

LION



RX1-A

<b>860-Lion receiver RX1-A</b>	
Article number:	860RX-MN-10B
Application areas:	Telphers, towing and recovery vehicles, dump bodies, agriculture machines a.o.
Frequency:	433 - 434 MHz (16 channels)
Mod. Type:	Narrow band FM-modulation
Coding:	Digital pulse code
Code comb.:	65.536
Relay output:	10 (4 x 2 + 2 x 1) + 2 for stop function Stop Relay; Potential free, close 8A AC I Function Relay; Potential free, open / close 16A AC I Function Relay 1-8; Momentary Function Relay 9-10; Momentary /Latching Simultaneous Interlocking functions
Radio type:	Double superheterodyne PLL synthesiser
Sensitivity:	-120 dBm ( 12 db SINAD )
Antenna:	External
Power supply:	12/24V AC/DC and 48/115/230V AC
Power consumption:	12V DC; 150 mA - 1 A                      24V DC; 60 - 600 mA 24V AC; 80 - 800 mA                      48V AC; 100 - 400 mA 115V AC; 70 - 200 mA                      230V AC; 25 - 100 mA
Weight:	Apr. 1.900 g (4.19 lb)
Dimensions:	256 x 217 x 85 mm (10.08 x 8.54 x 3.35) in incl. mounting brackets
Protection:	IP 65
Recommended transmitter:	860-Lion TX1-A

**TELE RADIO AB**  
Sweden, Main office  
Tel. +46 (0)31-748 54 60  
e-mail: info@tele-radio.com

[www.tele-radio.com](http://www.tele-radio.com)

**TELE RADIO SVERIGE**  
Sweden  
Tel. +46 (0)31-724 98 00  
e-mail: sverige@tele-radio.com

**TELE RADIO OÜ**  
Estonia  
Tel. +372 44 511 55  
e-mail: eesti@tele-radio.com

**TELE RADIO GmbH**  
Germany  
Tel. +49 (0)94 51-944 8 550  
e-mail: deutschland@tele-radio.com

**TELE RADIO ASIA**  
China  
Tel. +86-(0)592-3111168  
e-mail: china@tele-radio.com

**TELE RADIO TURKEY**  
Turkey  
Tel. +90 216 574 22 94  
e-mail: turkiye@tele-radio.com

**TELE RADIO LTD**  
England  
Tel. +44 (0) 1625 509125  
e-mail: england@tele-radio.com

**TELE RADIO LLC**  
North America & Latin America  
Tel. +1 (305) 459 0763  
e-mail: america@tele-radio.com

**TELE RADIO BV**  
Benelux  
Tel. +31-(0)70-419 41 20  
e-mail: benelux@tele-radio.com

**TELE RADIO AS**  
Norway  
Tel. +47-6933 4900  
e-mail: norge@tele-radio.com