

LION



TX2-A

860-Lion transmitter TX2-A	
Article number:	860TX-12-0xC
Application areas:	Cranes, EOT cranes, hoists, towing and recovery vehicles, crusher, dump bodies, load changers, agriculture machines a.o.
Frequency:	433 - 434 MHz (69 channels)
Mod. Type:	Narrow band FM-modulation
Coding:	Digital pulse code
Code comb.:	65.536 (factory coded)
Functions:	24 (12x2) On / Off
Output:	10m W (50 ohm)
Antenna:	Built-in
Power supply:	Exchangable rechargeable battery (Li-ion)
Operating time:	Apr. 24 hrs. continuous use
Weight:	Apr. 300 g (0,66 lb)
Dimensions:	210 x 80 x 40 mm (8.27 x 5.12 x 5.51 in)
Protection:	IP 65
Recommended receiver:	860-Lion RX2-A, RX3-A and RX4-A

TELE RADIO AB
Sweden, Main office
Tel. +46 (0)31-748 54 60
e-mail: info@tele-radio.com

www.tele-radio.com

TELE RADIO SVERIGE
Sweden
Tel. +46 (0)31-724 98 00
e-mail: sverige@tele-radio.com

TELE RADIO OÜ
Estonia
Tel. +372 44 511 55
e-mail: eesti@tele-radio.com

TELE RADIO GmbH
Germany
Tel. +49 (0)94 51-944 8 550
e-mail: deutschland@tele-radio.com

TELE RADIO ASIA
China
Tel. +86-(0)592-3111168
e-mail: china@tele-radio.com

TELE RADIO TURKEY
Turkey
Tel. +90 216 574 22 94
e-mail: turkiye@tele-radio.com

TELE RADIO LTD
England
Tel. +44 (0) 1625 509125
e-mail: england@tele-radio.com

TELE RADIO LLC
North America & Latin America
Tel. +1 (305) 459 0763
e-mail: america@tele-radio.com

TELE RADIO BV
Benelux
Tel. +31-(0)70-419 41 20
e-mail: benelux@tele-radio.com

TELE RADIO AS
Norway
Tel. +47-6933 4900
e-mail: norge@tele-radio.com